

KAPA Energie

Q2400

Pure Sine Wave Inverter



PORTABLE POWER STATION

— All-in-One Solar Energy Storage System —

Super Quick Solar Charge

Outdoor/Household Use

Q2400



PHONE CHARGER
10 Wh
113 CHARGES



LED LIGHT
10W
125 HOURS



PROJECTOR
100W
12.5 HOURS



LAPTOP CHARGER
63 Wh
20 CHARGES



TELEVISION
50W
24 HOURS



REFRIGERATOR
50W
24 HOURS



COFFEE MACHINE
1400W
186 CUPS



ELECTRIC DRILL
900W
1.35 HOURS

Power



2400W

Inverter



Pure Sine Wave

SPECIFICATIONS

Rated Capacity	1324W/h
Inverter	Pure sine wave
Output Port	USB-A(5V/2.4A)x3 USB-C(PD 100 W max.)x1 AC x 2 (2400W output power, 4000W surge Power)
Car Port	N/A
DC Input	N/A
Solar Charge	Anderson Power Port (APP),13-100V, 25A max. 1300W MPPT
AC Charge	1300W
AC Input	Total 2400W
Uninterruptible Power Supply Response Time	<12ms
LCD	Yes
Size	434 mm x 314 mm x 272 mm
Weight	22.5kg
Standard accessories	AC charging cord+ user manual+ MC4 adapter

CALCULATION

Power Station Wattage ÷ Appliance Wattage = Hours of Continuous Use

Appliance usage calculations are based off single appliance usage on power stations. Combining appliances will reduce the duration of usage of the power station.